

NBG-12LR and NBG-12LRA

Dual-Action Agent Release Stations



Releasing Panels

General

The NBG-12LR and NBG-12LRA are Agent Release Stations designed for use with NOTIFIER Fire Alarm Control Panels with releasing capabilities.

Features

- Non-coded, dual-action operation.
- Made with durable polycarbonate.
- Optional surface backbox.

NBG-12LRA

- Abort switch.
- Power-on indication.
- Released indication.
- Manual release (dual-action).

NBG-12LR

- Dual-action release only.

Applications

The NBG-12LRA and NBG-12LR are ideal for areas such as clean rooms and computer rooms where a chemical agent is used to extinguish a fire.

Specifications

- **Temperature Range:** 32°F to 120°F (0°C to 49°C).
- **Relative Humidity:** 10% to 93% (noncondensing).
- **For use indoors in a dry location.**

Product Line Information

NBG-12LRA: Agent release station with abort switch, Release LED, and Normal LED.

NBG-12LR: Dual-action agent release station.

SBA-10: Surface backbox for NBG-12LRA, metal. Dimensions 4.5" (11.43 cm) W x 8.188" (20.8 cm) L x 1.375" (3.49 cm) D.

SB-10: Surface backbox for NBG-12LR, metal. Dimensions 4.125" (10.48 cm) W x 5.5" (13.97 cm) L x 1.375" (3.49 cm) D.

SB-I/O: Surface backbox for NBG-12LR, plastic.

BG12TR: Optional trim ring for semi-flush mounting.

Agency Listings and Approvals

In some cases, certain modules may not be listed by certain approval agencies, or listing may be in progress. *Consult factory for latest listing status.*

- **UL/ULC Listed:** S692.
- **MEA Listed:** 67-20-E.
- **FM Approved.**
- **CSFM:** 7150-0028:0199.
- **FDNY:** COA#6114 (NFS2-3030), COA#6121 (NFS2-640, NFS-320).
- **U.S. Coast Guard, Lloyd's Register, American Bureau of Shipping (ABS):** For information on marine applications, see DN-60688.



Dual Action NBG-12LR



Dual Action NBG-12LRA

NOTIFIER® and **FlashScan®** are registered trademarks of Honeywell International Inc.
©2014 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.

For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118.
www.notifier.com
